FREECOM

DVB-T SCART

DIGITAL TERRESTRIAL TV & RADIO RECEIVER / SCART

Watch Digital TV on any TV with the Freecom DVB-T SCART receiver.

- Watch "free to air" Digital TV and Listen to "free to air" Digital Radio on your conventional TV set.
- Fits behind any TV because of smart hinge design.
- Channel scan and name recognition.
- Electronic program guide (EPG) system.
- DVB-T antenna.
- Antenna connection fits your existing analogue antenna.
- Installs in seconds.
- Small dimensions (only 13,5x5,5x1,75 cm).
- Full size remote control
- AC3 compatible.
- All Freecom devices meet the highest industry standards.
- Unlimited free helpdesk support.
- 2 years manufacturers warranty.

The Freecom DVB-T SCART receiver brings you into the world of Digital TV

The DVB-T TV standard sends Digital Signals (TV and RADIO) "free to air". With the Freecom DVB-T SCART receiver, you can watch Digital TV on your conventional TV set.

The days of a set top box sticking out under your expensive LCD or Plasma TV are over. Because of the smart hinge design, the Freecom DVB-T SCART Receiver is easy to hide behind your (flatscreen) TV without the use of extra cables. Just plug the Freecom DVB-T SCART receiver directly into the SCART input on your TV, switch it on, pick up the remote control and enjoy "free to air" digital television. Because of its ultra compact size you can take the Freecom DVBT SCART anywhere you go. You will be amazed of how such a small receiver allows you to access free digital TV (including Teletext) and radio wherever you are.

DVB is a registered trademark of the DVB Project.

FREECOM

Free your mind

PRODUCT SPECIFICATIONS FREECOM DVB-T SCART RECEIVER:

INTERFACE	SCART
DIMENSIONS	135x55x17.5 mm / 5.31 x 2.16 x 0.69 inch
WEIGHT	115g 4.05 ounce
KEY FEATURES	Digital Terrestrial TV and Radio Program Reception Support DVB Protocol (ETS 300 744) Supports HDTV/AC3 standards Supports EPG (where available) Supports Teletext (where available, not available in UK) Multi-Channel Preview Channel Auto Scan Decoding MPEG-I, MPEG-II
TV ENCODER	NTSC-M, PAL- (B/D/G/H/I/M/N)
DVB-T PARAMETERS	Carrier type: 2K or 8K Guard interval: 1/4, 1/8, 1/16 or 1/32 Code rate: 1/2, 2/3, 3/4, 5/6 or 7/8 Modulation: QPSK, 16QAM or 64QAM Channel Bandwidth: 6MHz, 7MHz, 8MHz
EXTERNAL ANTENNA CONNECTOR	Input Terminal: 75 Ohm
TUNER	Receiving frequency: VHF174~230MHz UHF470~862MHz
ENVIRONMENTAL SPECIFICATIONS	Operating + 5° to + 50° C Storage –20° to 60° C Gradient 20° C / hour (max.) Humidity Operating 8 – 80% (non-condensing)
POWER REQUIREMENTS	Pluggable power supply 230 VAC/ 50Hz to 5 VDC
RECEIVER REQUIREMENTS	Available terrestrial signal in your region, TV with SCART input

Ref. MM/PW/27-10-2006

PACKAGE INCLUDES:

- Freecom DVB-T SCART Receiver
- External DVB-T antenna
- Pluggable power supply 230V AC
- Remote Control, infrared cable
- Quick install guide
- Freecom manual
- 2 Years manufacturers warranty and unlimited helpdesk support

Art. No. EU	28353
EAN code EU	4021801283535
Color	Black

2 YEARS MANUFACTURERS WARRANTY

DVB Digital Video Broadcasting

TNT

All devices meet the highest industry standards; CE, FCC and RoHS